

XL-2T

7 Zone Control/Communicator

control communicator

CE



Designed for easy installation and homeowner convenience, the fully-featured XL-2T control panel is the next generation of the popular XL-2 series. For price and performance, it's the best control panel in its class.

Remote or local troubleshooting is made quick and simple with the XL-2T's large event buffer. The control panel is engineered to maintain up to 76 events, each of which is identified with a time and date stamp.

XL-2T features seven fully programmable zones

Features like Fast Reporting, Fire Verification, Auto-Arming and a Built-in Siren Driver save time and money on every installation.

Features:


- ◆ Unattended downloading
- ◆ 7 fully programmable zones
- ◆ 78 event history with time and date stamp
- ◆ Auto arming options based on AC real time clock
- ◆ 2 programmable trigger outputs
- ◆ 2 channel siren driver built in
- ◆ 2 Fully programmable entry timers
- ◆ SIA false alarm reduction features
- ◆ Bell supervision
- ◆ Temporal bell option

PERIPHERALS



CE

CE2R
Wireless Remote-Control Keyfob



TAM-1
Telephone Access Module



Chatbak-V
Verbal Status Module

- Stand-alone or place next to any FBIII keypad
- Gives system status of your alarm in easy-to-understand English
- One button arming station in home or away modes
- Family/office message center

XL-2T

SYSTEM COMPONENTS:

XL-2TLT: Includes Control/Communicator. Transformer and Keypads available separately

XL-2T: Includes Control/Communicator and 12V 20VA Transformer

XL-2TX: PC Board only

XK-406: 6 zone LED keypad, surface mount, individual LEDs for zones and system status. (Also available, model XK-206)

XL-4600RM: 6 zone LED metal keypad, flush mount, individual LEDs for zones and system status

XL-4600SM: 6 zone LED plastic keypad, surface mount, individual LEDs for zones and system status

XK-5LC: 2 line by 12 large characters LCD supertwist backlit display. (Also available, model XK3LC)

XK-7LC: 2 line by 12 large characters LCD supertwist backlit display, includes armed status LED

6615: 6 zone LED legend style keypad, surface mount individual LEDs for zone and system status

Note: If you use XL-4600RM, XL-4600SM or 6615 you cannot use any other types

SPECIFICATIONS:

Zones:

- ◆ 7 fully programmable zones, each selectable for EOL supervision, NO or NC devices
- ◆ Four emergency keypad conditions (fire, panic, aux, duress)
- ◆ Versatile zone types:
Controlled zone types include; Instant, exit/entry, interior, day, and keyswitch, with options for fast loop response, restore and chime by zone. 24 hour zone types include: fire, burglary, silent, trouble, medical
- ◆ Programmable central station reporting codes per zone
- ◆ Smoke reset and verification features
- ◆ Cross zone capabilities
- ◆ New stay delay zone type

Additional Features:

- ◆ Cancel code feature
- ◆ Installer walk test feature
- ◆ Real time clock with reminder when time needs to be reset
- ◆ Chime on/off feature through keypad
- ◆ Keypad tamper function with optional CS transmission
- ◆ Swinger shutdown option
- ◆ System stabilization time prevents false alarms during powerup
- ◆ NFPA temporal bell
- ◆ Arm while faulted
- ◆ Supervised bell output
- ◆ 78 Event Log
- ◆ Paging Format

User Codes:

- ◆ 15 user codes
- ◆ Ambush and door strike codes
- ◆ Open/close by user ID
- ◆ Unique O/C codes for all users

Programming/Remote Operations:

- ◆ Remote commands include: arm, disarm, bypass zones, change user codes, read system status
- ◆ Remote operations can be performed through PC Downloader

- ◆ Upload/download remote operations of all system features and functions. ALL ON A SINGLE CALL. With FBIII Answering Machine Bypass
- ◆ Remote and/or unattended downloading
- ◆ On-site programming directly through keypad (LED or LCD)
- ◆ CSID and installer code, anti-takeover feature

Keypads:

- ◆ Individual LEDs show status of each zone with indications of ALARM, TROUBLE BYPASS and NOT READY conditions
- ◆ English LCD keypad displays system status in 2 line by 16 character readout with customized 12 character zone descriptors (LCD keypads include XK-5LC, XK-3LC and XK-7LC)

Central Station Communications:

- ◆ Two CS account numbers (3 or 4 digits)
- ◆ Pulse formats include: 3x1, 4x1, 4x2, Expanded: Speeds 10, 20, 40PPS with or without parity
- ◆ FBI Superfast, Ademco Express 4x1 and 4x2 Formats, Ademco CID Format
- ◆ Split and dual reporting option for openings and closings
- ◆ Test options include daily, weekly, 27, 60 or 90 day, hourly intervals test by time, event

Power Specifications:

- ◆ Watchdog circuitry insures integrity of microprocessor
- ◆ Total aux. power: 500 mA. regulated
- ◆ Transformer: 12V 20VA

Listings:*

- ◆ Residential UL Household Combination Burglary/Fire (XL-2T)
- ◆ UL Mercantile Burglary Listing: Local Grade A, Police Connect Grade A, Grade AA
- ◆ California State Fire Marshal (CSFM)*
- ◆ CE

*Listing pending as of printing date